MABA-008757-CT1160

1:1 Transmission Line Transformer 4.5 to 3000 MHz

Features

- Surface mount .
- Wide frequency range
- 1:1 Impedance
- Lead free
- RoHS Compliant and is 260°C reflow compatible
- Available on tape and reel, reel quantity 2000

Description

The MABA-008757-CT1160 is a 1:1 Transmission Line Transformer. The windings of the MABA-008757-CT1160 are welded to the package substrate for improved reliability and to eliminate lead content. This Transformer is ideally suited for CATV and Satellite STB/Subscriber applications.



Pin Configuration


Function	Pin Number		
Secondary Dot	1		
Not Connected	2		
Secondary	3		
Primary	4		
Primary Dot	5		

Ordering Information


Part Number	Package	
MABA-008757-CT1160	2000 piece reel	
MABA-008757-CT11TB	Customer Test Board	

ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions

Schematic



Case Style SM-22B



Dimensions are inches (millimeters) ±0.015 (0.38) unless otherwise specified.

hined herein without notice.

North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400 India Tel: +91.80.4155721 • China Tel: +86.21.2407.1588

Visit www.macomtech.com for additional data sheets and product information.

M/A-COM Technology Solutions for and its affiliates reserve the right to make

ir formation

is considering for development. Performance is based on target specifications, simulated results,

ailable

ching

and/or prototype measurements. Commitment to develop is not guaranteed. PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples

Commitment to produce in volume is not

1

Tech nology Solut

M/A-COM Products

Part Status: ETRR, Rev. V1



1:1 Transmission Line Transformer 4.5 to 3000 MHz

M/A-COM Products Part Status: ETRR, Rev. V1


Electrical Specifications: : $T_A = 25^{\circ}C$, $Z_0 = 50\Omega$

Parameter	Test Conditions	Units	Min.	Тур.	Max.
Frequency Range	4.5 – 3000 MHz				
Insertion Loss 1 (Pin 4 to Pin 3)	4.5 – 1000 MHz 1000 – 2000 MHz 2000 – 2500 MHz 2500 – 3000 MHz	dB dB dB dB	-	0.07 0.63 1.93 4.20	1.0 2.0 5.0 6.5
Insertion Loss 2 (Pin 4 to Pin 1)	4.5 – 1000 MHz 1000 – 2000 MHz 2000 – 2500 MHz 2500 – 3000 MHz	dB dB dB dB	_	0.29 0.08 2.00 5.30	1.0 2.0 6.0 8.4
Amplitude UnBalance (Nominal 0dB)	4.5 – 20 MHz 20 – 1000 MHz	dB dB	_	±1.0 ±0.3	±1.2 ±1.0
Phase UnBalance (Nominal 180°)	4.5 – 1000 MHz	0	_	±0.03	±20
Input return Loss (Pin 4)	4.5 – 1000 MHz	dB	16	26.30	_

Absolute Maximum Ratings ^{1,2}

Parameter	Absolute Maximum		
RF Power	250 mW		
DC Current	30 mA		
Operating Temperature	-40° C to +85° C		
Storage Temperature	-40° C to +85° C		

Suggested Footprint



PCB FOOTPRINT

ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed. PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are MA-COM Techniol gy Solutions for and its infiliates reserve the right to make On ing st to the products to information contained herein without notice. typical. Mechanical outline has been fixed. Engineering samples a Commitment to produce in volume is not duardited. my bg available.

Visit www.macomtech.com for additional data sheets and product information.

2

[•] North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400 • India Tel: +91.80.4155721 • China Tel: +86.21.2407.1588

MABA-008757-CT1160




1:1 Transmission Line Transformer 4.5 to 3000 MHz

M/A-COM Products Part Status: ETRR, Rev. V1


Typical Performance Curves @ $T_A = 25^{\circ}C$, $Z_0 = 50\Omega$


Insertion Loss 1 (Pin4 - Pin3)




1 0 - 1 -2 B -3 -4 -5 -6 -7 504 1003 1502 2001 2501 3000 4.5 Frequency (MHz)

Insertion Loss 2 (Pin4 - Pin1)






Phase Balance



Return Loss: Input



North America Tel: 800.366.2266
Europe Tel: +353.21.244.6400
India Tel: +91.80.4155721
 Visit www.macomtech.com for additional data sheets and product information.

- ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed. **PRELIMINARY**: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or restored multiple Commitment to produce in volume is not **duranteed**.
 - MA-COM Technol gy Squtions no and is iffiliates reserve the right to make on ingre to the product's to information contained herein without notice.