

# **VCO-109S/STC**

#### HIGH RELIABILITY MILITARY AND SPACE VCO

Package: Module, 22.86mmx22.86mmx13.97mm




#### **Features**

- 900 MHz to 1800 MHz VCO
- 15V Operation
- +12.5dBm Typical Output Power
- -90dBc/Hz at 10kHz
- -112dBc/Hz at 100kHz
- -135 dBc/Hz at 1000 kHz

## **Applications**

- Instrumentation
- Aerospace
- Test Equipment
- Plug and Play



Functional Block Diagram

## **Product Description**

RFMD's VCO-109S/STC is a hybrid assembled voltage controlled oscillator integrated into a connectorized module. The VCO-109 features an integrated resonator and tuning varactors. The part features excellent performance over temperature.

#### **Ordering Information**

VCO-109S/STC High Reliability Military and Space VCO

# Optimum Technology Matching® Applied ☐ GaAs HBT ☐ SiGe BiCMOS ☐ GaAs pHEMT ☐ GaN HEMT ☐ GaAs MESFET ☐ Si BiCMOS ☐ Si CMOS ☐ BIFET HBT ☐ InGaP HBT ☐ SiGe HBT ☑ Si BJT ☐ LDMOS

RF MICRO DEVICES®, RFMD®, Optimum Technology Matching®, Enabling Wireless Connectivity™, PowerStar®, POLARIS™ TOTAL RADIO™ and UltimateBlue™ are trademarks of RFMD, LLC. BLUETOOTH is a t mark owned by Bluetooth SiG, Inc., U.S.A. and licensed for use by RFMD. All other trade names, trademarks and registered trademarks are the property of their respective owners. ©2006, RF Micro Devices,

# **VCO-109S/STC**



#### **Absolute Maximum Ratings**

Parameter	Rating	Unit
Supply Voltage (V <sub>CC</sub> )	17	V
V <sub>TUNE</sub>	0 to 22	V
Storage Temperature	-65 to 150	°C
Operating Temperature	-55 to 100	°C
ESD JESD22 - A114 Human Body Model (HBM)		V



Caution! ESD sensitive device.

Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical performance or functional operation of the device under Absolute Maximum Rating conditions is not implied.

RoHS status based on EU Directive 2002/95/EC (at time of this document revision).


The information in this publication is believed to be accurate and reliable. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents, or other rights of third parties, resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

Parameter	Specification		Unit	0 100		
Parameter	Min.	Тур.	Max.	Unit	Condition	
Frequency	_					
Frequency Range	900		1800	MHz	100% Production Tested	
Tuning Voltage						
900MHz	0	1.2		V <sub>DC</sub>	100% Production Tested	
1800MHz		18.5	20	V <sub>DC</sub>	100% Production Tested	
Tuning Sensitivity						
900MHz	61.2	81.6	102	MHz/V	100% Production Tested	
1125MHz	44.3	59.1	73.9	MHz/V	100% Production Tested	
1350MHz	49.1	65.5	81.9	MHz/V	100% Production Tested	
1575MHz	41.8	55.6	69.6	MHz/V	100% Production Tested	
1800MHz	17.6	23.5	29.4	MHz/V	100% Production Tested	
Output Power	10	12.5	16	dBm	100% Production Tested	
Output Phase Noise						
10kHz		-90	-84	dBc/Hz	100% Production Tested	
100 kHz		-112	-106	dBc/Hz	100% Production Tested	
1000 kHz		-135	-129	dBc/Hz	100% Production Tested	
Power Supply	14.75	15	15.25	٧	100% Production Tested	
Supply Current		15.0	18.0	mA	100% Production Tested	
Harmonic Suppression						
2nd Harmonic		-15	-10	dBc	100% Production Tested	
3rd Harmonic		-15	-10	dBc	100% Production Tested	
Spurious (Non-Harmonic)			-80	dBc		
Frequency Pushing		4	6	MHz p-p	14.75V to 15.25V	
Frequency Pulling		20	25	MHz p-p	20dB RL	
Output Impedance		50		Ω		
3dB Modulation Bandwidth	15000	20000		kHz	Z <sub>G</sub> =50Ω	
Tune Port Impedance (DC)		50		kΩ		



Pin	Function	Description
1	VTUNE	Tuning voltage.
2	vcc	Supply voltage.
3	RF Output	VCO RF output.

## **Pin Out and Package Drawing**



PINOUT	FUNCTION				
PIN	vco	MIXER	POWER DIVIDER		
1	TUNING VOLTAGE	RF PORT	OUT 2		
2	SUPPLY VOLTAGE	X PORT	IN		
3	RF OUTPUT	LO PORT	OUT 1		

