

Item	Num	Lvl	Rev	WJ Part Number	Description	MFR Part Number	CAGE Code	Qty	Per	Ref Desg	Mfr Name
0	1	-		452632-000	REF. ASSY. APP BOARD. HIGH-POWER AMPLIFIER					.0000	
0	1	--1		452960-000	REF. FP31QF APP BOARD. FINAL TEST REQUIREMENTS					.0000	
1	1	--4		452354-001	FAB. HEAT SINK					1.0000	
2	1	-		860000-608	SCREW. MCH. SKTHD. ALN. 2-56. 0.188. SS	070206CHSCAZZ				6.0000	FASTENER SERVICE
3	1	-		034031-000	WASHER. SPLIT. #2. MEDIUM. SS	MS35338-134	96906			6.0000	MILITARY STD
4	1	-		850000-703	WASHER. FLAT. #2. SMALL. SS	25089X0149X016XCAZZ	NONE			6.0000	FASTENER SERVICE
6	1	-B		412724-017	CAP. 2PF. +/-0.05PF. 50V. ACCU-P. SMD. 0603	06031J2R0ABTTR	04222	2.0000		C2	AVX
						06035J2R0AAWTR	04222			C3	AVX
						06035J2R0ABTTR					AVX
7	1	-A		412720-017	CAP. 22PF. 5PCT. 50V. NPO/COG. SMD. 0603	06035A220JAT1A	04222	4.0000		C1	AVX
						500R14N220JV4E	29454			C10	JOHANSON DIELECTRICS
						ECUY1H220JCV	0J4G8			C4	PANASONIC
						GMC10CG220J50NT				C8	CAL-CHIP
						GRM39COG220J050AL					MURATA
						LC-CC410603CG220J5NT					LAUBE
8	1	-		861000-459	RES. 5.1. 5PCT. 1/16W. CHIP. SMD. 0603	ERJ-3GSYJ5R1V		1.0000		R1	PANASONIC
						RM06J5R1CT					CAL-CHIP
9	1	-		862000-567	IND. 12NH. 5PCT. CER CORE. SMD. 0805. SRF 4000MHz	0805CS-120XJBC		2.0000		L1	COILCRAFT
										L2	
10	1	-		860000-523	IND. 4.7NH. +/-0.3NH. MULTILAYER. SMD. 0603. 4800MHZ	CTLL1608-4N7S		1.0000		L3	CENTRAL TECHNOLOGIES
						LL1608-FH4N7S					TOKO
11	1	-A		412720-037	CAP. 1000PF. 5PCT. 50V. X7R. SMD. 0603	06035C102JAT1A	04222	2.0000		C11	AVX
						500R14W102JV4E	29454			C7	JOHANSON DIELECTRICS
						ECUY1H102JBV	0J4G8				PANASONIC
						GMC10X7R102J50NT					CAL-CHIP
						GRM39X7R102J050AL					MURATA
12	1	-		850000-200	CAP. 0.1UF. 10PCT. 50V. X7R. SMD. 1206	12065C104KAT1A		1.0000		C12	AVX
						500R18W104KV4E					JOHANSON DIELECTRICS
						ECJ-3VB1H104K					PANASONIC
						ECU-Y1H104KBW					PANASONIC
						GMC31X7R104K50NTM					CAL-CHIP
						GRM426X7R104K050AL					MURATA
13	1	-B		412721-093	RES. 51.0. 5PCT. 1/16W. CHIP. SMD. 0603	CRCW0603510JRT2	0J4G8	1.0000		R2	DALE
						ERJ3GSYJ510H	59124				PANASONIC
						LR-HPWAJ0510TS0					LAUBE
						RM73B1JTE510J					KOA
14	1	--1		FP31QF-F ** SUB ** FP31QF	HFET. 2WATT. GAAS.. DC-3GHZ. 6X6MM QFN HFET. 2WATT. GAAS. DC-3GHZ. 6X6MM QFN			1.0000		Q1	
15	1	-		445930-001	REF. NO LOAD PART			12.0000		C1	
										C10	
										C2	
										C3	
										C4	
										C5	
										C6	
										C8	
										L1	

Item Num	Lvl	Rev	WJ Part Number	Description	MFR Part Number	CAGE Code	Qty	Per	Ref Desg	Mfr Name
									L2	
									L3	
									R1	
16	1	-	862000-422	CONN. RF. SMA. F. STRT. FLANGE MOUNT. 1	142-0701-851		2.0000		J1	JOHNSON COMPONENTS
									J2	
17	1	-	862000-138	CONN. DC. HDR. STRT. TH. 1	2101-3-00-01-00-00-07-0		3.0000		J3	MIL-MAX
									J4	
									J5	
18	1	-	452924PC	PCB. APP BOARD, FP31QF. 24 BOARDS/PANEL			.0417			

Report successfully completed